

LED Premium-Tape 1200



IP
20

24 V DC

80 W

L70/B10 ≥ 50.000 h

L	Wattage
500	9,6 W
1000	19,1 W
1500	28,3 W
2000	37,2 W
3000	53,6 W
4000	68,0 W
5000	80,0 W

z.B. Einfräsprofil 34 mm
e.g. Milled Profile 34 mm

ø8 mm

LED 24V/...W

Montage- und Bedienungsanleitung

Hera LED Linienleuchte

Typ LED Premium-Tape 1200

Bestimmungsgemäße Verwendung

Selbstklebende, flexible LED Streifen. Als Möbelleuchte gemäß VDE 0710 Teil 14/04.82 zum Einbau in Möbel zugelassen.



- Beim Austausch von defekten Teilen dürfen nur Originalteile verwendet werden.
- Alle Steckverbindungen immer bis zum Anschlag einführen.
- Polung beachten (Aufdruck auf LED Tape)!
- Die Clipse sind nach der Verrastung nicht mehr zu öffnen!
- Die Lichtquelle dieser Leuchte ist nicht ersetzbar; wenn die Lichtquelle ihr Lebensdauerende erreicht hat, ist die gesamte Leuchte zu ersetzen.
- Die Leuchte nicht demontieren da das Licht der Leuchtdioden das menschliche Auge verletzen kann.
- Nur zum Anschluss an Hera LED Trafos 24V zugelassen: Tape mit einem Stecker (2-pol. Anschlussleitung) max. 100 W Ausgangsleistung, Tape mit Doppelstecker (4-pol. Anschlussleitung) max. 200 W Ausgangsleistung
- max. 80 W bzw. 5 m pro Anschlussleitung (nur bei angelöteter Anschlussleitung)
- Die Streifen lassen sich ohne zu löten (bis max. 3 m) mit dem Verbindungsclip oder den Leitungen kontaktieren.
- Da es bei höheren Leistungen zu Spannungsabfällen und daraus resultierenden Lichtstärkeunterschieden zwischen dem Anfang und dem Ende eines Streifen kommen kann, sollten bei Lichtbändern diese immer „Anfang an Anfang“ und „Ende an Ende“ zusammen montiert werden.
- Werden andere als die angegebenen LED - Konverter eingesetzt, übernimmt Hera keine Gewährleistung.
- Für trockene, saubere, hochenergetische Oberflächen (keine pulverlackierten Bleche) geeignet. Weitere Verarbeitungshinweise auf der Produktseite unter www.hera-online.de.



erhältliches Zubehör:

- Anschlussleitung LED Tape 1200
- Verbindungsclip LED Tape 1200
- Verbindungsleitung LED Tape 1200



Entsorgen Sie elektrische Geräte nicht im Hausmüll, nutzen Sie die Sammelstellen in Ihrer Gemeinde. Wenn Sie das Gerät durch ein neues ersetzen, ist der Verkäufer gesetzlich verpflichtet, das alte mindestens kostenlos zur Entsorgung entgegenzunehmen.

Nachdruck auch auszugsweise verboten.

Erklärung der Symbole: <http://www.hera-online.de/de/fachliches.html>

Assembly and operating Instructions

Hera LED Linear Luminaire

Type LED Premium-Tape 1200

Intended use

Pressure-sensitive, flexible LED strips. Approved as a furniture luminaire in accordance with VDE 0710 part 14/04.82 for installation in furniture.



- Faulty parts should only be replaced with original parts.
- Always fully insert all plug connections.
- Observe the correct polarity (print on LED Tape)!
- The clip can't be open after the clip is locked together!
- The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire must be replaced.
- Do not disassemble the luminaire as the light diode can cause damage to the eyes.
- Only approved for connection to Hera LED transformers 24V: Tape with single plug (2-pole supply cable) max. 100 W output power. Tape with double plug (4-pole supply cable) max. 200 W output power
- maximum 80 W or 5 m per supply cable (only with supply cable solder on tape)
- The Tapes can be reconnected without soldering (up to 3 m max.) with the connecting clips or cables.
- A high output within one light strip can lead to voltage drop and can cause differences in the light-output between the beginning and the end of the light strip. In this case - for the use of several light strips in one light row - please mount "the beginning together with the beginning" and "the end together with the end".
- Hera grants no warranty when other LED converters as the prescribed converters are used.
- Suitable for dry, clean, high-level surfaces (no powder coated sheets).



available accessories:

- supply cable LED Tape 1200
- connecting clip LED Tape 1200
- connecting cable LED Tape 1200



Do not dispose of electrical appliances in household waste, use separate collection facilities. When replacing old appliances with new ones, the retailer is obliged by law to accept to take back your old appliance for disposal free of charge.

Reproduction of this document in whole or part is forbidden.

Explanation of the Symbols: <http://www.hera-online.de/en/technical-information.html>